



Optional wired remote control for use with PST Series 1500-3000W inverter models.

| Inverter |
|----------|
| Remote   |
| Control  |

Model RC-300

## **Design Features**

- LCD displays AC Volts, AC Amps, frequency, power (watts), and power factor
- LED Indicators for overload, over temperature and power
- Includes 25' cable
- Sold separately

## **2 YEAR LIMITED WARRANTY**

|                              | MODEL NO.                   | RC-300  |
|------------------------------|-----------------------------|---|
| COMPATIBLE<br>INVERTERS      | MODEL NUMBERS               | PST-1500-12, PST-1500-24, PST-1500-48<br>PST-2000-12, PST-2000-24<br>PST-3000-12, PST-3000-24<br>PST-300S-12E, PST-300S-24E |
| DISPLAY                      | LCD DISPLAY                 | AC Voltage (V), AC Current (A), Frequency (Hz), Active Power (Watts), Apparent Power (VA) and Power Factor (PF)             |
|                              | LED INDICATORS              | Overload, Over Temperature and Power  |
| INPUT / OUTPUT<br>CONNECTION | CABLE SET                   | RJ-50 (10p10C) with crossed-over / rolled-over connections<br>Length: 7.6 Metres / 25 Feet                                  |
| ENVIRONMENT                  | OPERATING TEMPERATURE RANGE | 0°C to 40°C / 32°F to 104°F   |
| DIMENSIONS                   | (W X H X D), MM             | 110 x 65 x 24.7   |
|                              | (W X H X D), INCHES         | 4.33 x 2.56 x 0.97  |
| WEIGHT                       | WEIGHT WITHOUT CABLE        | 85 g / 0.04 lbs   |
|                              | WEIGHT WITH CABLES          | 256 g / 0.12 lbs  |

NOTE: Specifications are subject to change without notice